

LESSON 1 AN/FCC-100(V)7 & 9X GETTING STARTED USING THE FRONT PANEL ASSEMBLY

IF PASSWORD PROTECTION HAS BEEN ENABLED WITH AN UNKNOWN PASSWORD, IT CAN BE OVERRIDEN FOLLOWING THE STEPS LISTED BELOW.

STEP	OPERATOR ACTION	MESSAGE DISPLAYED	SELECT
1	<p>Turn "ON" the AN/FCC-100. Then the display changes to the SW REV LEVEL (version number). Within four (4) seconds after the change from SW REV LEVEL to INITIALIZING the user presses in this order:</p> <p align="center">PREV ENTRY STORE NEXT ENTRY RESTART</p> <p>If the Password was successfully Overridden the display will show Password Overridden.</p>	<p>INITIALIZING</p> <p>SW REV LEVEL 12.3</p> <p>PASSWORD OVERRIDDEN</p>	

PROGRAM PORTS 1 THROUGH 16 FOR THE UNUSED MODE OF OPERATION AND THE CAU CONFIGURATION FOR DISABLED.

STEP	OPERATOR ACTION	MESSAGE DISPLAYED	SELECT
1	Press the RESTART key.		
2	Press the NEXT ENTRY P key.	ACTIVATE	
3	Press the NEXT ENTRY P key.	EXAMINE	
4	Press the NEXT ENTRY P key. (Select CONFIGURE using the DOWN B arrow key).	CONFIGURE	CONFIGURE

LESSON 1 AN/FCC-100(V)7 & 9X GETTING STARTED USING THE FRONT PANEL ASSEMBLY

STEP	OPERATOR ACTION	MESSAGE DISPLAYED	SELECT
5	Select OFFLINE using the DOWN ⏴ arrow key.	OFFLINE	OFFLINE
6	Select A-CONFIG using the DOWN ⏴ arrow key.	A-CONFIG	A-CONFIG
7	If selection displayed is not PORT 1 , then scroll through the options by pressing the NEXT ENTRY ⏵ key until PORT 1 is displayed. (Select PORT 1 using the DOWN ⏴ arrow key).	SYSTEM PORT 1	PORT 1
8	If selection displayed is not UNUSED , then scroll through the options by pressing the NEXT ENTRY ⏵ key until UNUSED is displayed. (Select UNUSED using the DOWN ⏴ arrow key).	UNUSED	UNUSED
9	Press STORE to " save " this UNUSED PORT 1 CONFIGURATION . Notice that PORT 1 is now flashing .	PORT 1	
10	Press the NEXT ENTRY ⏵ key. Notice that PORT 2 is now flashing . (Select PORT 2 using the DOWN ⏴ arrow key).	PORT 2	PORT 2
11	If selection displayed is not UNUSED , then scroll through the options by pressing the NEXT ENTRY ⏵ key until UNUSED is displayed. (Select UNUSED using the DOWN ⏴ arrow key).	UNUSED	UNUSED
12	Press STORE to " save " this UNUSED PORT 2 CONFIGURATION . Notice that PORT 2 is now flashing .	PORT 2	
13	Press the NEXT ENTRY ⏵ key. Notice that PORT 3 is now flashing . (Select PORT 3 using the DOWN ⏴ arrow key).	PORT 3	PORT 3

LESSON 1 AN/FCC-100(V)7 & 9X GETTING STARTED USING THE FRONT PANEL ASSEMBLY

STEP	OPERATOR ACTION	MESSAGE DISPLAYED	SELECT
14	If selection displayed is not UNUSED , then scroll through the options by pressing the NEXT ENTRY P key until UNUSED is displayed. (Select UNUSED using the DOWN B arrow key).	UNUSED	UNUSED
15	Press STORE to " save " this UNUSED PORT 3 CONFIGURATION . notice that PORT 3 is flashing .		
16	"REPEAT" STEPS 13 through 15 for PORTS 4 through 16.		
17	Press the NEXT ENTRY P key until CAU is displayed. (Select CAU using the DOWN B arrow key).	CAU	CAU
18	Then scroll through the options by pressing the NEXT ENTRY P key until DISABLED is displayed. (Select DISABLED using the DOWN B arrow key).	DISABLED ENABLED	DISABLED
19	Press STORE to " save " this CAU CONFIGURATION .		
20	Press the RESTART key.		

**END OF AN/FCC-100(V)7 & 9X PORTS 1 THROUGH 16
UNUSED AND CAU DISABLED CONFIGURATIONS.**

LESSON 1 AN/FCC-100(V)7 & 9X GETTING STARTED
USING THE FRONT PANEL ASSEMBLY

The NEXT ENTRY \bar{P} key means "NO"
you DO NOT want this selection.

The DN ENTRY β key means "YES"
you WANT this selection.

RESTART returns the front panel
assembly to Operate mode,
canceling the command in
progress.